



Fusibile 1000V DC gBAT

*1000V DC gBAT fuse*

## FUSIBILI NH A COLTELLO PER BATTERIE – TIPO gBAT – TENSIONE 1000V DC

*BLADE TYPE FUSES FOR BATTERIES - gBAT TYPE - VOLTAGE 1000V DC*

| grandezza   | codice IW      | $I_n$ (A)                | $V_n$ (V)                | $P_w$ (W)                | $I^2t$ tot. (A <sup>2</sup> s)               | $I_k$ (kA)                | conf.        |
|-------------|----------------|--------------------------|--------------------------|--------------------------|----------------------------------------------|---------------------------|--------------|
| <i>size</i> | <i>IW code</i> | <i>I<sub>n</sub> (A)</i> | <i>V<sub>n</sub> (V)</i> | <i>P<sub>w</sub> (W)</i> | <i>total I<sup>2</sup>t (A<sup>2</sup>s)</i> | <i>I<sub>k</sub> (kA)</i> | <i>pack.</i> |
| <b>NH-1</b> | <b>1699200</b> | 200A                     | 1000V DC                 | 27                       | 29.000                                       | 30kA                      | 3            |
| <b>NH-2</b> | <b>1699199</b> | 200A                     | 1000V DC                 | 26                       | 29.000                                       | 30kA                      | 3            |
|             | <b>1699250</b> | 250A                     | 1000V DC                 | 36                       | 38.000                                       | 30kA                      | 3            |
| <b>NH-3</b> | <b>1699161</b> | 160A                     | 1000V DC                 | 38                       | 10.000                                       | 30kA                      | 3            |
|             | <b>1699201</b> | 200A                     | 1000V DC                 | 45                       | 20.000                                       | 30kA                      | 3            |
|             | <b>1699251</b> | 250A                     | 1000V DC                 | 48                       | 40.000                                       | 30kA                      | 3            |
|             | <b>1699315</b> | 315A                     | 1000V DC                 | 54                       | 80.000                                       | 30kA                      | 3            |
|             | <b>1699350</b> | 350A                     | 1000V DC                 | 55                       | 90.000                                       | 30kA                      | 3            |
|             | <b>1699400</b> | 400A                     | 1000V DC                 | 58                       | 138.000                                      | 30kA                      | 3            |